

Updating the PLA schema and Create Layout RBA action parameters

For version 11.0, there is no update to the schema from version 10.0. However, for sites upgrading from 8.0.x, the following steps are necessary to acquire the changes that were made in version 8.2. For information on additional rules in PLA and updating any of the action parameters specific to those rules, see the latest [PLA Administrator Guide](#).

Reminder for MIS users: When schema updates occur, please review and modify the MIS program to output XML that conforms to the latest PLA schema. Kodak does not provide programming services for specific MIS systems.

1. On the Prinergy Workflow primary server, start Workshop.
2. Select **Tools > Rule Set Manager (RBA)**.
The Rule Set Manager window appears.
3. Select **Tools > RBA XML Schema Manager**.
The XML Data Model Schema Manager window appears. The PLA schema appears under **Browsing 'General'**, and is called **Target XML**.
4. Click the **update/delete** link next to **Target XML**.
5. In the **Schema File** field, click **Browse**, and then locate `TargetXML.xsd` in `C:\ProgramFiles(x86)\Kodak \LayoutAutomation\RBA\XML`.
This is the updated PLA schema that was placed by the installer.
6. Click **Open** to load the schema.
7. In the Update/Delete Schema window, select **Update Schema**.
Note: The **Schema File:** box goes blank, but the schema is updated.