

Digital Job Ticket Editor—Exceptions tab

Note: Options on this tab may vary depending on the selected digital device. Some of the settings or setting values may not be available. Also, there may be additional settings available for specific devices which are not documented here.

On the **Exceptions** tab you can add special pages to the job such as a cover or an insert or change the settings of a range of pages in the job. These pages will have different settings from the rest of the pages in the job.

The options in the Digital Job Ticket Editor are based on the capabilities of the selected device. When the Prinergy server connects to a digital device via Setup, the device communicates its capabilities in JMF format. The values for the different parameters are updated in the Setup application per device, and are reflected in the Digital Job Ticket Editor. The default value that was set on the digital device (and can be viewed in Setup) is used as the default value per parameter. If no value was set as default, the Job Ticket Editor displays **Device Default**. This selection can be changed.

When you define settings that are in conflict, these settings are marked with a red line around them, and when you hover above them, a tool tip displays what is wrong with the defined settings. You can also click the **Constraints** tab to see which settings you need to change in order to print the job.

Note: If you make a change in the Setup application while the Digital Job Ticket Editor is open, you must close and reopen the Digital Job Ticket Editor to see the change in the Digital Job Ticket Editor.

Insert

To include an insert in the job, on the **Exceptions** tab, click **Insert...**, and in the Insert dialog box, define the settings for the insert, and click **Save**.

Cover

To include a cover in the job, on the **Exceptions** tab, click **Cover...**, and in the Cover dialog box, define the settings for the cover, and click **Save**.

Page Range

To change the settings for a range of pages in the job, click **Page Range...**, and in the Page Range dialog box, define the settings for the cover, and click **Save**.