

# Upgrading the firmware



1. In Proofer Viewer, click the **Maintenance** button.
2. Click the **Service**
3. In the **Service Tree**, navigate to **Scripts > Scripts**.
4. Run the following script: Kodak\Proofer Client\ JavaScripts\ MachineControl\ update\_dsp\_firmware.js.
5. When prompted whether to auto-detect the DSP device type, click **Yes**.

The firmware upgrade takes about two minutes per device.

1. In the Scripting view, look at the Output pane to confirm that each DSP successfully upgraded.
- If the upgrade is successful, disconnect the USB cable from the Proofer Controller, wait two seconds, and then reconnect it. Exit the Service window.
  - If the upgrade was unsuccessful, contact a service representative.